

7-2-2 自治系統(一)介面設定



✦ 網路架構檔案

◆ 自治系統網路(一)_空白.pkt

✦ 路由器介面設定

```
R1(config)#int fa0/1
R1(config-if)#ip address 192.168.100.1 255.255.255.0
R1(config-if)#no shutdown
R1(config-if)#exit
R1(config)#int fa1/0
R1(config-if)#ip address 192.168.0.254 255.255.255.0
R1(config-if)#no shutdown
Router(config)#do show ip int brief
```

✦ 測試連線

◆ 自治系統網路(一)介面

```
Interface IP-Address OK? Method Status Protocol
FastEthernet0/0 unassigned YES unset administratively down down
FastEthernet0/1 192.168.100.1 YES manual up up
FastEthernet1/0 192.168.0.254 YES manual up up
```

```
C:\>ping 192.168.0.254 [OK]
C:\>ping 192.168.100.1 [OK]
C:\>ping 192.168.100.2 [NO]
```

